



MultiMeters

ST2000PC Mini Pocket Multimeter

Basic Function	Range	Best Accuracy
DC Voltage	200mV/2V/20V/200V/600V	$\pm(0.5\%+2)$
AC Voltage	200mV/2V/20V/200V/600V	$\pm(0.8\%+2)$
DC Current	200 μ A/2000 μ A/20mA/200mA	$\pm(1.8\%+5)$
AC Current	200 μ A/2000 μ A/20mA/200mA	$\pm(1.8\%+3)$
Resistance	200 Ω /2k Ω /20k Ω /200k Ω /2M Ω /20M Ω	$\pm(1.0\%+3)$
Temperature	Indoor temperature	
Special Functions		
Auto Range		v
Diode		v
Continuity Buzzer		v
Data Hold		v
Sleep Mode		v
Low Battery Display		v
Max. Display		1999



ST2000

ST-4000ZA 10A AC/DC with μ A Auto Range Digital Multimeter

Basic Function	Range	Best Accuracy
DC Voltage	400mV/4V/40V/400V/600V	$\pm(0.5\%+2)$
AC Voltage	400mV/4V/40V/400V/600V	$\pm(1.0\%+2)$
DC Current	400 μ A/4000 μ A/40mA/400mA/4A/10A	$\pm(1.2\%+3)$
AC Current	400 μ A/4000 μ A/40mA/400mA/4A/10A	$\pm(1.5\%+3)$
Resistance	400 Ω /4k Ω /40k Ω /400k Ω /4M Ω /40M Ω	$\pm(1.0\%+2)$
Capacitance	40nF/400nF/4 μ F/40 μ F/100 μ F	$\pm(2.5\%+5)$
Frequency	10Hz/100Hz/1KHz/10KHz/100KHz/1MHz/10MHz	$\pm(0.1\%+5)$
Duty Cycle	1%~99%	
Special Functions		
Auto Range		v
Diode		v
Continuity Buzzer		v
Data Hold		v
Sleep Mode		v
Low Battery Display		v
Max. Display		3999



ST4000ZA